



บริษัท เอดีดี เฟอร์เนส จำกัด

**ADD FURNACE CO.,LTD.**

44 ซอยบรมราชชนนี 70 ถนนบรมราชชนนี แขวงศาลาธรรมสพน์ เขตทวีวัฒนา กรุงเทพฯ 10170

โทร: 02-888-3472 โทร: ออกแบบ:08-08-170-170 แฟกซ์: 02-888-3258

https://www.add-furnace.com E-mail: [sales@add-furnace.com](mailto:sales@add-furnace.com)

**XIMADEN SCR POWER REGULATOR PAC30A**

**XIMADEN PAC30A**



1. PAC30 A- Three-phase power regulator	Control signal input: 4-20 mA, voltage regulator adjustment resolution: 0.2. ; From the slow, slow stop time: 15 seconds; relay alarm contact output Radiator 80 °C over-temperature alarm; external voltage limits, manual / automatic external start and stop	
2. Load connection	Y T-	Three-phase star centers do not take the N or triangular pure resistive load 380VAC±0% 50HZ ±5%
	Y N-	Three-phase pure resistive load the center of the star-connected N 380VAC ± 10% 50 HZ ±5% ★ is not recommended to use the center then N, the neutral current
3. Load current and shape Note: inductive load Select current rating Should be derated 2-3 Times.Silicon carbide Load derating 1/2	40A	Constant resistive load 40A the following (natural cooling)
	60A	Constant resistance load 60A the following air-cooled
	80A	Constant resistance load 80A the following air-cooled
	120A	Constant resistance load 120A the following air-cooled
	150A	Constant pure resistance load 150A air-cooled
4. Users of the PWM had zero adjustment function (control options) ★ external start-stop switch U1 instead. Can not be selected via an external switch to select the voltage regulator / power adjustment conversion ★ inductive load	0	None
	U01	Zero-power adjustment cycle 2 seconds