



บริษัท เอดีดี เฟอร์เนส จำกัด

ADD FURNACE CO.,LTD.

44 ซอยบรมราชชนนี 70 ถนนบรมราชชนนี แขวงศาลาธรรมสพน์ เขตทวีวัฒนา กรุงเทพฯ 10170

โทร: 02-888-3472 โทร: ออกแบบ:08-08-170-170 แฟกซ์: 02-888-3258

https://www.add-furnace.com E-mail: sales@add-furnace.com

XIMADEN SCR POWER REGULATOR

PAC01A

XIMADEN PAC01A



1. PAC01A- Single- phase power re gulator	Control signal input: 4 ~ 20mA; adjust the resolution: the regulator 0.2. ; With auxiliary voltage adjustment and external start and stop; slow starting, slow stop time: 15 seconds; heat sink over-temperature alarm 80 °C, OC gate output.		
Load power and synchronization voltage ★	1-	110VAC ± 10% 50HZ ± 8%	
	2-	220VAC ± 10% 50HZ ± 8%	
	3-	380VAC ± 10% 50HZ ± 8%	
3.Load current N ote: According to the actual load current taken the whole sele cted I nductive load and silicon carbide nonlinear loads should be 2-3 times the use of derating	40-	Constant resistive load 40A the following (natural cooling)	
	60-	Constant resistance load 60A the following air-cooled	
	80-	Constant resistance load 80A the following air-cooled	
	120-	Constant resistance load 120A the following air-cooled	
	150-	Constant pure resistance load 150A air-cooled	
4. W hen the heater break alarm HB Note: can instantly detect power failures, slow start, to avoi d power up / down transformer, high surge v oltag e and current "crash" accident	0	None	
	1	Heating load break alarm (inductive loads must be selected)	
5. U sers of the PWM had zero adjustment function (control options) ★ select the voltage regulator / power adjustment via an external switch U1 ★ inductive load can not be selected	0	None	
	U01	Zero-power adjustment cycle 2 seconds	